



ARKÉ: 12V 50-60Hz buzzer grey

19375

Wiring devices / Traditional wiring devices / ARKÉ / Devices

12V 50-60Hz buzzer grey

Buzzer, 12 V~ (SELV) 50-60 Hz, grey

Product Status

2 - Will be discontinued

Minimum order quantity


10 NR

Video


- [Arké lives in your time](#)




Drawings



Space view



Backside view



3D View

Gallery



Technical data

- **Class group:** Optical and acoustic signalling equipment
- **Class:** Buzzer
- **Nominal voltage:** 12 V
- **Type of current:** AC
- **Electricity consumption:** 0,67 A
- **Degree of protection (IP):** IP40
- **Loudness:** 75 dB
- **Housing colour:** Grey
- **Mounting method:** Other
- **Built-in transformer:** No

Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



8 007352 414938

Code 8007352414938
Quantity 1 NR
Dim. 5.1x2.8x5.3 [cm]
Weight 47.1 [g]



8 007352 414945

Code 8007352414945
Quantity 10 NR
Dim. 14.4x11.6x6 [cm]
Weight 514.4 [g]



8 007352 637795

Code 8007352637795
Quantity 120 NR
Dim. 36.5x33x13.5 [cm]
Weight 6,588 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).