



ARKÉ: 120V 50-60Hz buzzer white

19377.B

Wiring devices / Traditional wiring devices / ARKÉ / Devices

120V 50-60Hz buzzer white

Buzzer, 120 V~ 50-60 Hz, white

Product Status

2 - Will be discontinued

Minimum order quantity


10 NR

Video


- [Arké lives in your time](#)




Drawings



Space view



Backside view



3D View

Technical data

- **Class group:** Optical and acoustic signalling equipment
- **Class:** Buzzer
- **Nominal voltage:** 120 V
- **Type of current:** AC
- **Electricity consumption:** 0,07 A

- **Degree of protection (IP):** IP40
- **Loudness:** 75 dB
- **Housing colour:** White
- **Mounting method:** Other
- **Built-in transformer:** No

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 19. NOM - Mexico
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352471603
Quantity 1 NR
Dim. 5.1x2.8x5.3 [cm]
Weight 43.8 [g]

Code 8007352471610
Quantity 10 NR
Dim. 14.4x11.6x6 [cm]
Weight 482.2 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).