



ARKÉ: 120V 50-60Hz buzzer Metal

19377.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

120V 50-60Hz buzzer Metal

Buzzer, 120 V~ 50-60 Hz, Metal

Product Status

2 - Will be discontinued

Minimum order quantity

10 NR



Alternative products




19372.SR.M - Bell/buzzer
120V 50-60Hz Metal


Video

- [Arké lives in your time](#)


Drawings



Space view



Backside view



3D View

Technical data

- **Class group:** Optical and acoustic signalling equipment
- **Class:** Buzzer

- **Loudness:** 75 dB
- **Housing colour:** Grey

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 19. NOM - Mexico
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352596177
Quantity 1 NR
Dim. 5.1x2.8x5.3 [cm]
Weight 43.3 [g]

Code 8007352596184
Quantity 10 NR
Dim. 14.4x11.6x6 [cm]
Weight 477 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).