



## ARKÉ: 2-way switch IoT connected mechanism

---

### 19592.0

Wiring devices / View Wireless wiring devices / ARKÉ / Devices

### 2-way switch IoT connected mechanism

View Wireless connected electronic switch mechanism with 100-240 V 50/60 Hz relay output for 500 W incandescent lamps, 100 W LED lamps, 250 VA electronic transformers, 120 W fluorescent lamps, local or remote control, double technology with Bluetooth® wireless technology 5.0 standard for the creation of View Wireless mesh system and Zigbee 3.0 standard, 1 input for external button for actuator control or to recall a scenario, RGB LED visible in darkness with brightness control, 100-240 V 50/60 Hz power supply, to be completed with 1-, 2- or 3-module Arké interchangeable buttons

- Configuration from View Wireless App for Bluetooth technology system and Amazon App for Zigbee technology
- Compatible with Alexa, Google Home and IFTTT, using the dedicated gateway or Zigbee hub



### Product Status

3 - Active

### Minimum order quantity

1 NR

You may also be interested in



19021 - Button 1M grey



19021.B - Button 1M white




19021.M - Button 1M Metal



19022 - Button 2M grey



19022.B - Button 2M white



19022.M - Button 2M Metal



19597 - IoT connected gateway 2M grey



19597.B - IoT connected gateway 2M white



19597.M - IoT connected gateway 2M Metal


## Sheets, Manuals, Documentation

- [Light multilanguage instructions sheet \(1221 kb\)](#)
- [Foglio istruzioni Full \(775 kb\)](#)
- [Feuille d'instructions Full \(777 kb\)](#)
- [Hoja de instrucciones Full \(775 kb\)](#)
- [Full instructions sheet \(772 kb\)](#)
- [Φυλλάδιο οδηγιών Full \(919 kb\)](#)
- [Anweisungsblatt Full \(776 kb\)](#)
- [Anweisungsblatt Full \(843 kb\)](#)
- [Manuale app View Wireless \(15556 kb\)](#)
- [Manuel appli View Wireless \(37703 kb\)](#)
- [Manual app View Wireless \(37528 kb\)](#)
- [Manual View Wireless app \(37579 kb\)](#)
- [Εγχειρίδιο τεχνικού εγκατάστασης \(37781 kb\)](#)
- [Installationsanleitung View Wireless \(37508 kb\)](#)


## Video

- [Creating-the-system](#)
- [Customisations](#)
- [Operation-in-Zigbee-mode](#)
- [Bluetooth-wifi-gateway](#)


## Drawings



Space view



Backside view



3D View

## Technical data

- **Class group:** Domestic switching devices
- **Class:** Installation switch
- **Wiring system:** Two-way switch
- **Method of operation:** Rocker/button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Number of modules (module system):** 1
- **Push button switch:** Yes
- **Number of rockers:** 1
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **With mounting plate:** No
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Blue
- **RAL-number (similar):** 7015
- **Label space/information surface:** Yes
- **Illumination:** Optional
- **Function lighting:** Control and orientation
- **Type of lighting:** LED not exchangeable
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 250 V
- **Feedback-signal contact:** No
- **Connection type:** Screwed terminal
- **Washing machine switch:** No
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 46,20 mm
- **Built-in depth:** 36,50 mm

## Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 19. NOM - Mexico
- 29. QCERT - Colombia
- 37. Marking - Morocco
- 37. Marking - Morocco
- 40. Bluetooth technology
- 42. Zigbee certified
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

# Packaging



**Code** 8007352628342  
**Quantity** 1 NR  
**Dim.** 5.2x3.5x5.3 [cm]  
**Weight** 45.8 [g]

**Code** 8007352628359  
**Quantity** 60 NR  
**Dim.** 27x23x12.5 [cm]  
**Weight** 2,944 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).