



# EIKON: 13A switched/fused connection unit grey

#### 20049.L

Wiring devices / Traditional wiring devices / EIKON / Devices

## 13A switched/fused connection unit grey

2P switched 13 A 250 V~ connection unit, warning unit, protection fuse, with built-in mounting frame for installation in British standard square flush mounting boxes and to complete with 3-module British standard cover plates, grey

#### **Product Status**

3 - Active


### Minimum order quantity

10 NR

### Sheets, Manuals, Documentation

Multilanguage instructions sheet (2022 kb)

## Drawings



Space view



Backside view





3D View

## Technical data

Class group: Domestic switching devices

**Class**: Installation switch

Wiring system: Off switch 1-pole Method of operation: Rocker/button

Assembly arrangement: Other

Number of modules (module system): 3

Push button switch: Yes Number of rockers: 1

Mounting method: Flush-mounted Type of fastening: Screw mounting

With mounting plate: No

Material: Plastic

Material quality: Thermoplastic Surface protection: Untreated

Surface finishing: Matt

Colour: Grey

RAL-number (similar): 7024

Label space/information surface: Yes

**Illumination**: Yes

Function lighting: Illuminated (on) Type of lighting: LED exchangeable

Suitable for degree of protection (IP): IP40

Nominal voltage: 250 V Rated current: 13,00 A Feedback-signal contact: No Connection type: Screwed terminal

Washing machine switch: No Device width: 82,50 mm Device height: 82,50 mm Device depth: 33,00 mm

Built-in depth: 20,40 mm

### Certifications

00. CE Marking - EU

08. ASTA - UK (download)

37. Marking - Morocco

43. UKCA mark - Great Britain

- 92. RoHS UAE
- 96. Electrotechnical expert (download)

99. WEEE Directive (download)

## Packaging



Code 8007352406940

Dim. Weight 106.4 [g]

Quantity 1 NR 8.5x3.9x8.6 [cm]



Code 8007352406957

Quantity 10 NR

20.7x18.5x9.6 [cm] Dim.

Weight 1,162 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.