



EIKON: MASTER dimmer 230V 700W/VA 2M grey

20140

Wiring devices / Traditional wiring devices / EIKON / Devices

MASTER dimmer 230V 700W/VA 2M grey

Dimmer, 230 V~ 50/60 Hz for: 40-700 W incandescent lamps, 40-700 VA ferromagnetic transformers, control and regulation with built-in push button or from peripheral NO push buttons, MASTER function for 20141, MOSFET+TRIAC technology, visible in darkness, protection fuse, grey - 2 modules

Product Status

2 - Will be discontinued


Minimum order quantity

5 NR

Sheets, Manuals, Documentation

FI - Foglio istruzioni ZIS_49400277A0 (2103 kb)

Drawings



Space view









Technical data

- Class group: Domestic switching devices
- **Class**: Dimmer
- Method of operation: Push button
- Type of load: Inductive load
- Applicable with button: Yes
- Applicable with movement sensor: No
- Applicable with presence indicator: No
- Applicable with time switch/timer: No
- Applicable with transmission button: No
- Applicable with infrared button: No
- Mounting method: Flush-mounted
- Type of fastening: Snapper mounting
- Material: Plastic

Packaging



Code	8007352387829
Quantity	1 NR
Dim.	6x5.4x5.3 [cm]
Weight	78.8 [g]

Code 8007352387836 Quantity 5 NR Dim. 17.2x13.1x6 [cm] Weight 451.8 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported.Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed.For the terms of use of the information on the product info sheet see Conditions of Use.

- Material quality: Thermoplastic
- Surface protection: Untreated
- Surface finishing: Matt
- **Colour**: Grey
- RAL-number (similar): 7024
- Transparent: No
- Suitable for degree of protection (IP): IP40
- Nominal voltage: 230,00 230,01 V
- Frequency: 50,00 60,00 HZ
- **Control voltage**: 230,00 230,01 V
- Device width: 44,80 mm
- Device height: 49,00 mm
- Device depth: 42,00 mm