



EIKON: SLAVE dimmer 230V 400VA 2M Next

20168.N

Wiring devices / Traditional wiring devices / EIKON / Devices

SLAVE dimmer 230V 400VA 2M Next

SLAVE dimmer, 230 V~ for: 40-400 VA at 50Hz, 40-300 VA at 60 Hz dimmable electronic transformers, with neutral terminal, control from 20167 and 14167, MOSFET+TRIAC technology, protection fuse, Next - 2 modules

Product Status

2 - Will be discontinued

Minimum order quantity


5 NR

Sheets, Manuals, Documentation


- [FI - Foglio istruzioni ZIS_49400274A0 \(1949 kb\)](#)




Drawings



Space view



Backside view



3D View


Technical data

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Other
- **Type of load:** Capacitive load
- **Applicable with button:** No
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Silver
- **RAL-number (similar):** 9022
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 230,00 - 230,01 V
- **Frequency:** 50,00 - 60,00 HZ
- **Control voltage:** 230,00 - 230,01 V
- **Device width:** 44,80 mm
- **Device height:** 49,00 mm
- **Device depth:** 42,00 mm

Certifications

- 37. Marking - Morocco
- 96. Electrotechnical expert ([download](#))

Packaging



Code 8007352388284
Quantity 1 NR
Dim. 6x5.4x5.3 [cm]
Weight 71.7 [g]

Code 8007352388291
Quantity 5 NR
Dim. 17.2x13.1x6 [cm]
Weight 414.7 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).