



EIKON: 2P+E 16A French SICURY outlet+cover Next

20212.C.N

Wiring devices / Traditional wiring devices / EIKON / Devices

2P+E 16A French SICURY outlet+cover Next

2P+E 16 A 250 V~ SICURY socket outlet, French standard, with cover, Next - 2 modules


Product Status

3 - Active


Minimum order quantity

10 NR


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Number of units:** 1
- **Number of modules (module system):** 2
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** Yes
- **With enhanced contact protection:** Yes
- **Label space/information surface:** Yes
- **Colour:** Silver
- **RAL-number (similar):** 9022
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** Yes
- **Over voltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 16 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device width:** 44,80 mm
- **Device height:** 49,00 mm
- **Device depth:** 35,90 mm

Certifications

- 00. CE Marking - EU
- 04. NF - France ([download](#))
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352431850
Quantity 1 NR
Dim. 5.1x4.3x5.3 [cm]
Weight 48.8 [g]



Code 8007352431867
Quantity 10 NR
Dim. 26.9x11.6x4.9 [cm]
Weight 558.8 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).