



## EIKON: TORCIA hand lamp 230V Next

---

### 20395.N

Wiring devices / Traditional wiring devices / EIKON / Devices

### TORCIA hand lamp 230V Next

TORCIA, electronic hand lamp with high-efficiency LED, supply voltage 230 V~ 50-60 Hz, automatic emergency device, replaceable rechargeable Ni-MH battery, 2 hours of operating range, Next - 2 modules


### Product Status

2 - Will be discontinued

### Minimum order quantity

10 NR

### Alternative products




20397 - TORCIA LED  
emergency lamp 2M




### Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(487 kb\)](#)


## Drawings



Space view



Backside view



3D View

## Gallery



## Technical data

- **Class group:** Luminaires
- **Class:** Emergency luminaire
- **Mounting method:** Built-in
- **Monitoring equipment:** None
- **With remote switch connection:** No
- **Power supply system:** Peripheral (individual battery)
- **Battery quality:** NiMH
- **Lamp type:** LED not exchangeable
- **With light source:** Yes
- **Housing material:** Plastic
- **Housing colour:** Silver
- **Material cover:** Without cover
- **Voltage type:** AC
- **Nominal voltage:** 230,00 - 230,01 V
- **Degree of protection (IP):** IP40
- **Protection class:** II
- **Max. system power:** 1,00 W
- **Width:** 44,80 mm
- **Height/depth:** 49,00 mm
- **Built-in height/depth:** 39,50 mm

## Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

# Packaging



**Code** 8007352287037  
**Quantity** 1 NR  
**Dim.** 6x5.4x5.3 [cm]  
**Weight** 84.47 [g]

**Code** 8007352287044  
**Quantity** 10 NR  
**Dim.** 28.1x13.1x6 [cm]  
**Weight** 918.17 [g]

**Code** 8007352657281  
**Quantity** 120 NR  
**Dim.** 38.5x29x30 [cm]  
**Weight** 11,498.04 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).