



### EIKON: Frame 2M without screws 71mm

#### 21603

Wiring devices / Traditional wiring devices / EIKON / Mounting frames

#### Frame 2M without screws 71mm

2-module mounting frame, without screws, for 60 mm fixing centres or 56x56 mm mounting box, modular, 71 mm distance between centres

- The honeycomb structure gives structural strength
- The slots in the corners enable fixing to the panel
- The hooking teeth encourage fixing in series for the installation of multiple modules
- Thanks to the central slots, the support can be fixed onto the wall level



### **Product Status**

3 - Active

### Minimum order quantity


50 NR

## You may also be interested in



21602.C - Cover 2M Eikon mount-frame

## Drawings







3D View

### Technical data

- Class group: Domestic switching devices
- Class: Holder for modular domestic switching devices
- Model: Flush-mounted
- Mounting method: Mounting with screw
- Mounting method of the module inserts: Front side
- Mounting direction: Horizontal and vertical
- Number of modules horizontal (module system): 2
- Number of modules vertical (module system): 1
- With built-in installation box: No

- With screws: No
- Suitable for mounting in round junction box 60 mm: No
- Flush-mounted installation: Yes
- Suitable for subfloor installation duct box: No
- Suitable for wall duct: No
- Suitable for mounting on DIN-rail 35 mm: No
- Material: Plastic
- Material quality: Thermoplastic
- Surface protection: Untreated

### Certifications

- 01. IMQ Italy (download)

- 15. CCC China (download)
- 29. QCERT Colombia
- 50. Product Environm. Profile
- 96. Electrotechnical expert (download)

## **Packaging**



Code Quantity Dim.

8007352421363 1 NR

**Dim.** 7.4x7.4x2 [cm] **Weight** 19.9 [g]



Code Quantity Dim. Weight

8007352421370 50 NR 29x25x10 [cm] 1,076 [g]



 Code
 8007352625921

 Quantity
 300 NR

 Dim.
 62x26x30 [cm]

 Weight
 6,456 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.