



EIKON: 1P 10AX 2-way switch Vintage satin gold

22004.88

Wiring devices / Traditional wiring devices / EIKON / Devices

1P 10AX 2-way switch Vintage satin gold

1P 10 AX 250 V~ Vintage 2-way switch, satin-finish gold. Max 100 W for self-ballasted lamps (IEC 60669-1:2017)


Product Status

3 - Active


Minimum order quantity

10 NR


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Single push button
- **Method of operation:** Push button
- **Number of rockers:** 1
- **Number of modules (module system):** 100
- **Number of poles:** 1
- **Nominal voltage:** 230 V
- **Rated current:** 10,00 A
- **With lighting:** No
- **With signal lamp:** No
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Metal
- **Material quality:** Brass
- **Anti-bacterial treatment:** No
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Gold
- **RAL-number (similar):** 1035
- **Transparent:** No
- **Label space/information surface:** Yes
- **Device width:** 22,30 mm
- **Device height:** 44,80 mm
- **Device depth:** 54,70 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 09. VDE - Germany ([download](#))
- 10. EAC Eurasian Customs Union
- 13. SNI - Indonesia
- 15. CCC - China ([download](#))
- 19. NOM - Mexico
- 20. IQC - Argentina
- 36. ISI - India
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352655355
Quantity 1 NR
Dim. 5.1x6.5x2.7 [cm]
Weight 33.3 [g]



Code 8007352655362
Quantity 10 NR
Dim. 14.5x11x7.4 [cm]
Weight 381.3 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).