



LINEA: Electromech.badge switch 2M black

30403.G

Wiring devices / Traditional wiring devices / LINEA / Devices

Electromech.badge switch 2M black

Upright electronic badge switch, 4 A 250 V~ NO change-over relay output (NON SELV), 120-230 V~ 50-60 Hz power supply, pocket lighting to be visible in darkness, trimmer for adjusting switch-off time after removing the card, black - 2 modules. Supplied without ISO card (badge)

Product Status

3 - Active


Minimum order quantity

1 NR


Sheets, Manuals, Documentation

- [Light Multilanguage instructions sheet \(709 kb\)](#)
- [Full Multilanguage instructions sheet \(1127 kb\)](#)


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Alarm installations, emergency call and signalling
- **Class:** Access control system
- **Standalone:** Yes
- **Networkable:** No
- **PC-binding:** No
- **Type of interface:** None
- **Reading strategy:** Data medium
- **Signalling:** None
- **Mounting method:** Flush-mounted
- **Operating voltage AC 50 Hz:** 250,00 - 250,01 V
- **Operating voltage AC 60 Hz:** 250,00 - 250,01 V
- **Operating temperature:** 5 - 35 °C
- **Degree of protection (IP):** IP20
- **Colour:** Black
- **Model:** Reader
- **Material:** Plastic
- **Power over Ethernet (PoE):** None
- **Width:** 44,80 mm
- **Height:** 52,80 mm
- **Depth:** 36,10 mm
- **Compatible with Apple HomeKit:** No
- **Compatible with Google Assistant:** No
- **Compatible with Amazon Alexa:** No
- **IFTTT support available:** No
- **VdS class:** None


Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352688667
Quantity 1 NR
Dim. 6x5.4x5.2 [cm]
Weight 55.45 [g]



Code 8007352688674
Quantity 10 NR
Dim. 60x40x32 [cm]
Weight 554.5 [g]



Code 8007352688681
Quantity 120 NR
Dim. 38.5x29x30 [cm]
Weight 6,654 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).