



PLANA: Three push buttons+actuator

R14545

Smart systems&products / By-me Plus / PLANA / Devices

Three push buttons+actuator

Spare control device with three simple push buttons and actuator with change-over relay output 8 A 120-230 V~, to be completed with 1 or 2 module interchangeable buttons - 3 modules

Product Status

3 - Active

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(582 kb\)](#)
- [By-me automation-fw Compatibility \(206 kb\)](#)



Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Other
- **Method of operation:** Push button
- **Number of rockers:** 3
- **Number of modules (module system):** 300
- **Number of poles:** 1
- **Nominal voltage:** 230 V
- **Rated current:** 8,00 A
- **With lighting:** Yes
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Glossy
- **Colour:** White
- **RAL-number (similar):** 9003
- **Transparent:** No
- **Label space/information surface:** Yes
- **Imprint:** None
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 67,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 46,90 mm

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352616868
Quantity 1 NR
Dim. 11.2x9.6x9.8 [cm]
Weight 155.71 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).