



ARKÉ: Two simple push buttons

R19520

Smart systems&products / By-me Plus / ARKÉ / Devices

Two simple push buttons

Spare control device with two simple push buttons, to be completed with 1 or 2 module interchangeable buttons - 2 modules

Product Status

3 - Active

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(979 kb\)](#)
- [By-me automation-fw Compatibility \(206 kb\)](#)




Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Other
- **Method of operation:** Push button
- **Number of rockers:** 2
- **Number of modules (module system):** 200
- **Number of poles:** 0
- **Nominal voltage:** 29 V
- **With lighting:** Yes
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Transparent:** No
- **Label space/information surface:** Yes
- **Imprint:** None
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 44,80 mm
- **Device height:** 49,00 mm
- **Device depth:** 36,10 mm

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352617278
Quantity 1 NR
Dim. 11.2x9.6x9.8 [cm]
Weight 98.7 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).