



Adaptors: Vert.S31 adaptor +3Universal outs white

RI.00316.B

Portable installation / Plugs and socket outlets / Adaptors / Residential adaptors

Vert.S31 adaptor +3Universal outs white

250 V~ SICURY vertical multiway adaptor - max 1500 W, 2P+T 16 A

German/French standard plug, three 2P+T 16 A universal Italian standard type P40 socket outlets, white

- Triple universal socket outlet P40
- Space-saving thanks to the side socket outlets directed to take up less space with the plugs inserted
- Staggered so that the product does not obstruct close socket outlets or switches



Product Status

3 - Active

Minimum order quantity


12 NR

You may also be interested in




RI.00315.B - Vert.S17
adaptor +3Universal outs
white


Drawings



Space view



Backside view



3D View

Gallery




Technical data

- **Class group:** Domestic switching devices
- **Class:** Plug adapter
- **Model:** Compact
- **With plug for AU/NZ/PG/AR (AS/NZS 3112) (type I):** No
- **With plug for BE/DE/NL/RU (protective contact CEE 7/4, type F):** Yes
- **With plug for FR (earth pin) (type E):** Yes
- **With plug for UK/HK (BS 1363) (type G):** No
- **With plug for IT (S/P 11):** No
- **With plug for IT (S/P 17) (type L):** No
- **With plug for US/CA/CN (NEMA 1-15) (type A):** No
- **With plug for US/CA/CN (NEMA 5-15) (type B):** No
- **Type of bus:** Other
- **Number of USB ports:** 0
- **Colour:** White
- **Nominal voltage:** 230,00 - 230,01 V
- **Nominal current:** 0,00 - 16,00 A


Certifications

- 00. CE Marking - EU
- 03. CSV-IMQ - Italy
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352613300
Quantity 1 NR
Dim. 1x1x1 [cm]
Weight 112.3 [g]



Code 8007352613225
Quantity 12 NR
Dim. 28.4x18.4x11.6 [cm]
Weight 1,475 [g]



Code 8007352613232
Quantity 144 NR
Dim. 38x58x37 [cm]
Weight 18,200 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).