



## Surface mounting components: By-alarm - 64-zone control unit 120V~

### 01703.120

Safety / By-alarm Plus / Surface mounting components / Non-modular components

#### By-alarm - 64-zone control unit 120V~

By-alarm programmable control panel that can be managed via display keyboard, power supply 120 V~ 60 Hz, 8 local inputs expandable to 64 via the expansion modules, 1 power supply output 13.8 Vdc 1.5 A expandable with additional power supply unit, 1 alarm relay output, 1 change-over relay output 3 A 24 V~ expandable with another 64 via expansion modules, complete with metal enclosure, surface mounting



2 - Will be discontinued

1 NR


- [Multilanguage instructions sheet \(527 kb\)](#)
- [Installation manual \(4593 kb\)](#)
- [Programming manual \(1783 kb\)](#)
  
- [SW\\_By-alarmManager-EN\\_REL-02.01\\_20201127.zip](#)
  
- [Integration with burglar alarm system](#)

- **Class group:** Alarm installations, emergency call and signalling
- **Class:** Central alarm panel for intrusion detection system
- **Number of detection groups:** 64
- **Integrated dial device:** No
- **Number of outputs for acoustic signal generators:** 2
- **Occurrence memory:** Yes
- **Operating voltage:** 120 V
- **Suitable for bus connection:** Yes

- **Radio connection:** No
- **With power adaptor:** Yes
- **Emergency power supply integrated:** Yes
- **Interface external:** Yes
- **Height:** 35.300,00 mm
- **Width:** 32.500,00 mm
- **Depth:** 12.600,00 mm

- 00. CE Marking - EU
- 37. Marking - Morocco

- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))



8 007352 548190

8007352548190  
1 NR  
37.5x33.5x13 [cm]  
5,513 [g]

Vimar