



## Shared components: Actuator 1-10Vdc LED 120-230V MARINE

**01975**

Smart systems&products / By-me Plus / Shared components / DIN devices

### Actuator 1-10Vdc LED 120-230V MARINE




Actuator with 1-10 Vdc 30 mA output for LED control, 120-230 V~ 2,5 A change-over relay output, supply voltage 120-230 V~ 50/60 Hz, for DIN (60715 TH35) installation, occupies 3 17,5 mm modules. For MARINE sector

3 - Active

1 NR



- [Instructions sheet \(153 kb\)](#)
- [By-me automation-fw Compatibility \(206 kb\)](#)



3D

- **Class group:** Installation bus systems
- **Class:** Dimming actuator for bus system
- **Bus system KNX:** No
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** Other
- **Radio frequent bidirectional:** No
- **Model:** Control module
- **Width in number of modular spacings:** 3

- **With bus connection:** Yes
- **Bus module detachable:** No
- **Local operation/hand operation:** No
- **With LED indication:** Yes
- **Number of outputs:** 2
- **Power boost suitable:** No
- **Type of load:** Universal and LED Retrofit
- **Voltage:** 120,00 - 230,00 V
- **Parallel-service possible:** No
- **Frequency:** 50,00 - 60,00 HZ
- **Degree of protection (IP):** IP20

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain

- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))



8007352431553  
 1 NR  
 11.7x10.8x7.1 [cm]  
 177 [g]

Vimar