



8000: Dimmer 230V 60-900W/60-300VA

08336

Wiring devices / Traditional wiring devices / 8000 / Devices

Dimmer 230V 60-900W/60-300VA

Dimmer, 230 V~ 50-60 Hz, for: 60-900 W incandescent lamps, 60-300 VA ferromagnetic transformers, without radio interference suppression filter, control and regulation by rotary potentiometer, visible in darkness. Not suitable for the installation on table mounting box 09933



2 - Will be discontinued

20 NR

- [Multilanguage instructions sheet \(213 kb\)](#)

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Turn button
- **Type of load:** Inductive load
- **Applicable with button:** No
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** White
- **RAL-number (similar):** 9001
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 230,00 - 230,01 V
- **Frequency:** 50,00 - 60,00 HZ
- **Control voltage:** 230,00 - 230,01 V
- **Device height:** 45,00 mm
- **Device depth:** 51,50 mm

• 10. EAC Eurasian Customs Union

• 99. WEEE Directive ([download](#))



8007352031500
1 NR
6x2.8x5.3 [cm]
38.6 [g]



8007352031517
20 NR
28.1x13.1x6 [cm]
852.67 [g]

Vimar