



## IDEA: SLAVE dimmer 120V white

### 16604.120.B

Wiring devices / Traditional wiring devices / IDEA / Devices

#### SLAVE dimmer 120V white




SLAVE dimmer 120 V~ 60 Hz for: 40-500 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, control from MASTER CFL-LED-Dimmer with bleeder, visible in darkness, white. Not for Isoset enclosures



2 - Will be discontinued

1 NR

- [FI - Foglio istruzioni ZIS\\_49400636A0 \(2838 kb\)](#)
- [SI - Schemi Installativi ZIS\\_120 V Insta \(2052 kb\)](#)



3D

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Other
- **Type of load:** Universal and LED Retrofit
- **Applicable with button:** No
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic

- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** White
- **RAL-number (similar):** 9001
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 120,00 - 120,01 V
- **Frequency:** 60,00 - 60,01 HZ
- **Control voltage:** 120,00 - 120,01 V
- **Device width:** 24,80 mm
- **Device height:** 50,10 mm
- **Device depth:** 51,00 mm

- 37. Marking - Morocco



8007352498211  
1 NR  
5.1x4.3x5.3 [cm]  
58.9 [g]



8007352498228  
5 NR  
14.4x11.6x6 [cm]  
342.2 [g]

Vimar