



ARKÉ: MASTER dimmer 120V Metal

19135.1.120.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

MASTER dimmer 120V Metal

Universal-dimmer 120 V~ 60 Hz, phase-cutting, for: 40-400 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, LED phase-cutting electronic transformers, ON/OFF control and built-in or from NO peripheral push buttons regulation, MASTER function for 19137.120, minimum brightness regulation, visible in darkness, Metal. Not for Isoset enclosures



3 - Active

1 NR

- [Light Multilanguage instructions sheet \(1283 kb\)](#)
 - [Full Multilanguage instructions sheet \(1406 kb\)](#)
 - [Multilanguage instructions sheet \(2498 kb\)](#)
-
- [Arké lives in your time](#)

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Turn button
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt

- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Transparent:** No
- **Nominal voltage:** 120,00 - 120,01 V
- **Connection type:** Screwed terminal
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 50,70 mm

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain

- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))



8 007352601420

8007352601420
1 NR
5.1x4.3x5.3 [cm]
54.2 [g]



8 007352603479

8007352603479
10 NR
26.9x11.6x4.9 [cm]
606 [g]

Vimar