



ARKÉ: Univ.MASTER rotary-dimmer 230V Metal

19136.1.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

Univ.MASTER rotary-dimmer 230V Metal

Universal-dimmer 230 V~ 50 Hz, phase-cutting, for: 40-400 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, LED phase-cutting electronic transformers, ON/OFF or built-in or from NO peripheral push buttons control, regulation by rotary potentiometer, MASTER function for 19137, minimum brightness regulation, visible in darkness, Metal. Not for Isoset enclosures






3 - Active

10 NR

• [Multilanguage instructions sheet \(2356 kb\)](#)

• [Arké lives in your time](#)



3D

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Turn button
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt

- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Transparent:** No
- **Nominal voltage:** 230,00 - 230,01 V
- **Connection type:** Screwed terminal
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 50,70 mm

- 00. CE Marking - EU
- 31. TISI - Thailand
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain

- 92. RoHS UAE
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))



8007352594227
1 NR
5.2x3.9x6.2 [cm]
56 [g]



8007352594234
10 NR
20.5x11.5x7 [cm]
622.8 [g]

Vimar