



## ARKÉ: MASTER dimmer 120V white

### 19136.120.B

Wiring devices / Traditional wiring devices / ARKÉ / Devices

#### MASTER dimmer 120V white

Dimmer 120 V~ 60 Hz for: 40-500 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps and LED electronic transformers, control with built-in push button or from NO peripheral push buttons, control and regulation by rotary potentiometer, MASTER function for 19137.120, minimum power control, visible in darkness, white. Not for IsoSet enclosures






2 - Will be discontinued

1 NR

• [FI - Foglio istruzioni ZIS\\_49400635A0 \(2873 kb\)](#)

• [Arké lives in your time](#)



3D

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Turn button
- **Type of load:** Universal and LED Retrofit
- **Applicable with button:** Yes
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** White
- **RAL-number (similar):** 9016
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 120,00 - 120,01 V
- **Frequency:** 60,00 - 60,01 HZ
- **Control voltage:** 120,00 - 120,01 V
- **Connection type:** Screwed terminal
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 61,30 mm

• 19. NOM - Mexico

• 37. Marking - Morocco



8 007352 498068

8007352498068  
1 NR  
5.2x3.9x6.2 [cm]  
59.5 [g]



8 007352 498075

8007352498075  
10 NR  
20.5x11.5x7 [cm]  
658.7 [g]

Vimar