



## ARKÉ: IR relay-switch 120V white

### 19181.120.B

Wiring devices / Traditional wiring devices / ARKÉ / Devices

### IR relay-switch 120V white




Automatic lighting switch with IR motion sensor, adjustable dusk/dawn sensor threshold and time-delay cycle, NO 6 A 120 V~ relay output, supply voltage 120 V~ 50-60 Hz, white

3 - Active

5 NR



- [Light Multilanguage instructions sheet \(834 kb\)](#)
- [Full Multilanguage instructions sheet \(859 kb\)](#)
- [Arké lives in your time](#)



3D

- **Class group:** Domestic switching devices
- **Class:** Electronic insert for domestic switching devices
- **Model:** Other
- **Assembly arrangement:** Modular device for domestic switching devices
- **Number of modules (module system):** 1
- **Radio-controlled:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)

- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** White
- **RAL-number (similar):** 9016
- **Transparent:** No

- 00. CE Marking - EU
- 19. NOM - Mexico
- 37. Marking - Morocco

- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))



8007352471146  
1 NR  
5.1x4.3x5.3 [cm]  
51.5 [g]



8007352471153  
5 NR  
14.4x11.6x6 [cm]  
303.7 [g]

Vimar