



ARKÉ: TV-RD-SAT single-conn.male out.1dB Metal

19300.01.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices




TV-RD-SAT single-conn.male out.1dB Metal

Coaxial TV-RD-SAT 5-2400 MHz socket outlet, single connection, with male connector, connection attenuation 1 dB, Metal. Allows the passage of d.c. current and control signals (24 V 500 mA max)

3 - Active

20 NR

- [Arké lives in your time](#)



3D



- **Class group:** Antenna and satellite technique
- **Class:** Antenna socket box
- **Model:** End socket
- **Cover:** None
- **Tap loss at 860 MHz:** 0,10 dB
- **Tap loss at 2150 MHz:** 0,20 dB
- **Number of outlets:** 1

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco

- **Suitable for remote power supply:** Yes
- **Type of fastening:** Snap mounting (engagement)
- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Surface protection:** Lacquered
- **Material:** Plastic

- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))



8 007352 598393

8007352598393
1 NR
4.1x2.8x5.3 [cm]
39.6 [g]



8 007352 598409

8007352598409
20 NR
21.4x11.6x6 [cm]
851.7 [g]



8 007352 634817

8007352634817
200 NR
30.5x25.5x22.5 [cm]
9,317 [g]



8 007352 750647

8007352750647
8,800 NR
120x80x105 [cm]
409,948 [g]