



ARKÉ: TV-RD-SAT through-line male out.10dB gre

19300.10

Wiring devices / Traditional wiring devices / ARKÉ / Devices



TV-RD-SAT through-line male out.10dB gre

Coaxial TV-RD-SAT 5-2400 MHz socket outlet, through-line, with male connector, connection attenuation 10 dB, grey

3 - Active

20 NR

- [Arké lives in your time](#)



3D



- **Class group:** Antenna and satellite technique
- **Class:** Antenna socket box
- **Model:** Loop-through socket
- **Cover:** None
- **Tap loss at 860 MHz:** 10,60 dB
- **Tap loss at 2150 MHz:** 9,90 dB
- **Number of outlets:** 1
- **Through loss at 860 MHz:** 2,20 dB

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco

- **Through loss at 2150 MHz:** 3,40 dB
- **Suitable for remote power supply:** No
- **Type of fastening:** Snap mounting (engagement)
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Surface protection:** Untreated
- **Material:** Plastic

- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))



8007352414549
1 NR
4.1x2.8x5.3 [cm]
50.1 [g]



8007352414556
20 NR
21.4x11.6x6 [cm]
1,061 [g]



8007352634947
200 NR
30.5x25.5x22.5 [cm]
11,070 [g]