



ARKÉ: TV-RD-SAT through-line outlet2outs white

19302.10.B

Wiring devices / Traditional wiring devices / ARKÉ / Devices

TV-RD-SAT through-line outlet2outs white




Coaxial TV-RD-SAT 5-2400 MHz socket outlet, through-line, demix, 2 outputs with male (TV-RD) and female F-type (SAT) connectors, connection attenuation 10 dB, white - 2 modules

3 - Active

10 NR

- [Multilanguage instructions sheet \(905 kb\)](#)

- [Arké lives in your time](#)



3D



- **Class group:** Antenna and satellite technique
- **Class:** Antenna socket box
- **Model:** TWIN end socket
- **Cover:** None
- **Tap loss at 860 MHz:** 11,20 dB
- **Tap loss at 2150 MHz:** 12,00 dB
- **Number of outlets:** 2

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco

- **Through loss at 860 MHz:** 2,00 dB
- **Through loss at 2150 MHz:** 2,80 dB
- **Suitable for remote power supply:** No
- **Type of fastening:** Snap mounting (engagement)
- **Colour:** White
- **RAL-number (similar):** 9016
- **Material:** Plastic

- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))



8007352455818
1 NR
5.1x4.3x5.3 [cm]
79.2 [g]

8007352455825
10 NR
26.9x11.6x4.9 [cm]
855.7 [g]