



ARKÉ: TV-FM-SAT single conn. 3outs grey

19303

Wiring devices / Traditional wiring devices / ARKÉ / Devices

TV-FM-SAT single conn. 3outs grey

Coaxial TV-FM radio-SAT 5-2400 MHz socket outlet, single connection, demix, 3 outputs with TV male and female FM radio and F-type (SAT) connectors, connection attenuation 1 dB, grey - 2 modules. Allows the passage of d.c. current and control signals (24 V 500 mA max) through the female connector




3 - Active

5 NR



- [Multilanguage instructions sheet \(485 kb\)](#)

- [Arké lives in your time](#)



3D



- **Class group:** Antenna and satellite technique
- **Class:** Antenna socket box
- **Model:** End socket
- **Cover:** None
- **Tap loss at 860 MHz:** 1,80 dB
- **Tap loss at 2150 MHz:** 1,30 dB
- **Number of outlets:** 3

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco

- **Suitable for remote power supply:** Yes
- **Type of fastening:** Snap mounting (engagement)
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Surface protection:** Untreated
- **Material:** Plastic

- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))



8007352436510
1 NR
5.1x4.3x5.3 [cm]
82.4 [g]

8007352436527
5 NR
14.4x11.6x6 [cm]
460.9 [g]