ARKÉ: KNX IR presence detector white

19850.B

Smart systems&products / KNX / ARKÉ / Devices

KNX IR presence detector white

Passive infrared motion detector, KNX standard, white - 2 modules

3 - Active

1 NR

, ,

- Light Multilanguage instructions sheet (527 kb)
- Full Multilanguage instructions sheet (569 kb)
- Manuale installatore (505 kb)
- Installer manual (440 kb)

- DB_ComandoSupervisione_KNX_REL-01.17_20230117.zip

- Arké lives in your time







3D

- **Class group**: Installation bus systems
- **Class**: Movement sensor for bus system
- **Bus system KNX**: Yes
- **Bus system KNX-RF (Radio Frequent)**: No
- **Bus system radio frequent**: No
- **Bus system LON**: No
- **Bus system Powernet**: No
- **Radio frequent bidirectional**: No
- **Model**: Movement sensor
- **Mounting method**: Flush-mounted
- **Material**: Plastic
- **Material quality**: Thermoplastic
- **Surface protection**: Untreated
- **Surface finishing**: Matt
- **Colour**: White
- **RAL-number (similar)**: 9016
- **Transparent**: No
- **With bus connection**: Yes
- **Staircase light controller**: Yes
- **Response value luminosity adjustable**: Yes
- **Max. reach sideways**: 10,00 m

- 00. CE Marking - EU
- 27. KNX
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert (download)
- 99. WEEE Directive (download)

8 007352 457867

8007352457867
1 NR
11.2x9.6x9.8 [cm]
98.7 [g]

Vimar