



EIKON: MASTER dimmer 120V Next

20135.1.120.N

Wiring devices / Traditional wiring devices / EIKON / Devices

MASTER dimmer 120V Next

Universal-dimmer 120 V~ 60 Hz, phase-cutting, for: 40-400 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps and LED phase-cutting electronic transformers, ON/OFF control and built-in or from NO peripheral push buttons regulation, MASTER function for 20137.120, minimum brightness regulation, visible in darkness, Next. Not for Isoset enclosures



3 - Active

1 NR

' ' ,

- [Multilanguage instructions sheet \(2498 kb\)](#)

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Push button
- **Type of load:** Universal and LED Retrofit
- **Applicable with button:** Yes
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic

- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Silver
- **RAL-number (similar):** 9022
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 120,00 - 120,01 V
- **Frequency:** 60,00 - 60,01 HZ
- **Control voltage:** 120,00 - 120,01 V
- **Connection type:** Screwed terminal
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 50,70 mm

- 00. CE Marking - EU
- 37. Marking - Morocco

- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))



8 007352576100
 1 NR
 5.1x4.3x5.3 [cm]
 58.3 [g]



8 007352576117
 10 NR
 26.9x11.6x4.9 [cm]
 646.3 [g]

Vimar