



EIKON: SLAVE dimmer 230V Next

20137.N

Wiring devices / Traditional wiring devices / EIKON / Devices

SLAVE dimmer 230V Next

SLAVE dimmer 230 V~ 50 Hz for: 40-500 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, control from MASTER Dimmer with bleeder (01873), Next. Not for IsoSet enclosures




2 - Will be discontinued



5 NR

- [FI - Foglio istruzioni ZIS_49400569A0 \(2910 kb\)](#)
- [Installation diagrams \(2458 kb\)](#)

- [New universal dimmers](#)




3D

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Other
- **Type of load:** Universal and LED Retrofit
- **Applicable with button:** No
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic

- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Silver
- **RAL-number (similar):** 9022
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 230,00 - 230,01 V
- **Frequency:** 50,00 - 50,01 HZ
- **Control voltage:** 230,00 - 230,01 V
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 51,00 mm

• 37. Marking - Morocco

• 96. Electrotechnical expert ([download](#))



8007352461123
1 NR
5.1x4.3x5.3 [cm]
57.3 [g]



8007352461130
5 NR
14.4x11.6x6 [cm]
332.9 [g]

Vimar