



## EIKON: MASTER dimmer 120-230V Next

---

### 20148.N

Wiring devices / Traditional wiring devices / EIKON / Devices

#### MASTER dimmer 120-230V Next


Dimmer, supply voltage 120-230 V~ 50-60 Hz for: 40-500/40-800 W incandescent lamps and 40-300/40-500 VA ferromagnetic transformers, control and regulation with built-in or from peripheral NO push buttons, MASTER function, TRIAC technology, visible in darkness, Next



2 - Will be discontinued

10 NR

- [Multilanguage instructions sheet \(270 kb\)](#)



- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Push button
- **Type of load:** Inductive load
- **Applicable with button:** Yes
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic

- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Silver
- **RAL-number (similar):** 9022
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 120,00 - 230,00 V
- **Frequency:** 50,00 - 60,00 HZ
- **Control voltage:** 120,00 - 230,00 V
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 52,40 mm

- 00. CE Marking - EU
- 43. UKCA mark - Great Britain

- 99. WEEE Directive ([download](#))



8007352291249  
1 NR  
5.1x4.3x5.3 [cm]  
52.53 [g]



8007352291256  
10 NR  
26.9x11.6x4.9 [cm]  
589.07 [g]

Vimar